

DIGITAL MIXER AMPLIFIER A-3248DM-AS 1

DESCRIPTION

The A-3248DM-AS is a high cost-performance mixer power amplifier suited for broadcasting paging or background music in schools, offices, shops, factories, mosques, churches and large rooms.

■SPECIFICATIONS * 0 dB = 1 V

* U UD — I V
100 − 240 V AC ∼ 50/60 Hz
99 W (AC operation at 1/8 maximum output without clip)
480 W
MIC 1:1 mV (-60 dB*), 600 Ω , balanced, phone jack, selectable to RJ45 MIC 2 - 3:1 mV (-60 dB*), 600 Ω , balanced, phone jack MIC 4:1 mV (-60 dB*), 600 Ω , balanced, phone jack, selectable to AUX 1 AUX 1:100 mV (-20 dB*), 10 k Ω , unbalanced, RCA pin jack, selectable to MIC 4 AUX 2:100 mV (-20 dB*), 10 k Ω , unbalanced, RCA pin jack MP3:LED Display, Support USB, SD/MMC Card (up to 32 GB), Bluetooth, Radio FM, Record
Speaker Out :Speaker output in screw type terminal Direct Line (selectable) :21 Ω (100 V) or 4 Ω Rec Out :0 dB*, 600 Ω , unbalanced, RCA pin jack
DC +21 V (MIC 1)
Over 60 dB
Under 1% at 1 kHz, 1/3 rated power
MIC 1 :Mutes other input signals by 0 - 30 dB attenuation
50 - 20000 Hz
Bass :± 10 dB at 100 Hz Treble :± 10 dB at 10 kHz
POWER, SIGNAL, PEAK, PROTECT
0 °C to +40 °C
Fan Cooling
Panel : ABS Resin, Black Case : Steel Plate, Black
420 (W) X 100.9 (H) X 357 (D) mm (16.54" X 3.97" X 14.06")
5.0 kg (11.02 lb)
Antenna FM radio (1m)1

APPEARANCE

