


■ DESCRIPTION

VX-1000 system IP Remote Microphone (VX-100RM) has the functions of initiating general broadcast, emergency broadcast and also can trigger the pattern broadcast task by pressing the key. Users can configure the network parameters, extend the number of units, and customize function keys through the VX-1000 Setting Software to achieve personalized configuration. Remote Microphone Extension (RM-110VX) unit can be connected to it, each expansion unit has 10 keys, users can add up to 9 pcs which has 100 function keys.

■ SPECIFICATIONS

Model	VX-100RM
Power Supply	DC24V/1A or PoE(IEEE 802.3at)
Consumption Current	≤200mA (single VX-100RM) ≤500mA (when connecting 9 set of RM-110VX)
Audio Input	Balanced, 1Vrms (Max:2Vrms) the input impedance is 10K Ω
Audio Output	Unbalanced, 1Vrms, Output impedance 10K Ω.
Monitor Speakers	1W
Frequency Response	20 ~ 20,000Hz
Volume Control	Microphone volume control, monitor speaker volume control
Number of Function Keys	10 keys by single unit, up to 100 keys (with 9 x RM-110VX)
Network Interface	RJ45 interface, 100BASE-TX, Auto MDI/MID-X
Network Protocol	TCP/IP、UDP、HTTP、ARP、RTP、ICMP、IGMP、SIP
Operating Temperature	0°C ~ +40°C
Operating Humidity	≤90%, no condensation.
Finish	ABS resin, black
Dimensions	190 (W) x 76.5 (H) x 215 (D)mm (without gooseneck microphone)
Weight	828 g

■ APPEARANCE



UNIT: mm SCALE: 1/4