



A-1240SS/A-1360SS MIXER POWER AMPLIFIERS



***Ideal for small scale PA application with the
5-zone and all call speaker selector***

A-1240SS (240W) & A-1360SS (360W) Mixer Power Amplifiers

TOA A-1240SS / A-1360SS are high performance mixer power amplifiers with a 5-zone speaker selector that is suitable for public address broadcasting or background music usage. An all call button allows broadcasting to be made to all 5 zones. They also come with output short circuit protection, and thermal protection circuitry to prevent failure due to overheat.

Features:

- 3 Mic inputs, 2 Aux inputs, 1 pre-output
- Speaker output of high impedance (100V line) and low impedance (4-16Ω)
- Muting function enables Mic 1 input to have priority over other inputs
- 5 zone speaker selector and 1 all call
- Bass and treble control
- 5-step LED signal indicator

Specifications

Model		A-1240SS AS		A-1360SS AS	A-1360MK2 AS
Power Source		AC 230 V 50/60 Hz			
Rated Output		240 W	360 W		360 W
Power Consumption		252 W	350 W		350 W
Frequency Response		50 - 18,000 Hz, ±3 dB			
Distortion		Less than 0.3% at 1 kHz, 1/3 Rated Power			
Inputs	MIC 1, MIC 2, MIC 3	-52 dBV (2.5 mV), 600 Ω, Unbalanced, Equivalent to Phone Jack			
	AUX 1, AUX 2	-10 dBV (316 mV), 10 kΩ, Unbalanced, RCA Pin Jack			
Outputs	Direct Line	4-16 Ω, 42 Ω (100 V)	4-16 Ω, 28 Ω (100 V)		4-16 Ω, 28 Ω (100 V), 13.6 Ω (70 V)
	Speaker Selector	5-zone selector (all zones simultaneously selectable), plug in screw / 1 all call			-
	Pre Out	0 dBV (1.0 V), 600 Ω, Unbalanced RCA Pin Jack			
S/N Ratio		Over 65 dB (MIC1 - MIC3), Over 75 dB (AUX 1 - AUX2)			
Tone Controls		Bass: ±10 dB at 100 Hz, Treble: ±10 dB at 10 kHz			
Muting		MIC 1 overrides other input signals with 0 - 40 dB attenuation by voice switch of MIC 1 input level			
Indicators		Power LED, Signal LED			
Finish		Panel: ABS Resin, Black / Case: Steel Plate, Black			
Dimensions		420 (W) x 110 (H) x 384 (D) mm			
Weight		12.8 kg	14.6 kg		14.6 kg
Accessory		AC power cord (1pc)			

Connection Example

Connection with 3-Wired Attenuator

A-1360MK2 (360W)

The A-1360MK2 (360W) mixer power amplifier is the non-speaker selector model.



Human Society with
Sound & Communication

TOA Electronics Pte Ltd

www.toa.com.sg

Specifications are subject to change without notice.
Printed in Singapore (65) 865-0112-01A